

## Pushbutton Transmitter Module PTM 210F

**The radio transmitter module from EnOcean enables the implementation of wireless remote controls without batteries. Power is provided by a built-in electro-dynamic power generator.**

Key applications are wall-mounted flat rocker switches with 1 or 2 rockers (with medial position), as well as handheld remote controls with up to 4 single pushbuttons

### Functional Principle

A common electro-dynamic energy transducer is actuated by a bow, which can be pushed from outside the module on the left or right by an appropriate pushbutton or switch rocker. When the energy bow is pushed down, electrical energy is created and a RF telegram is transmitted including a 32-bit module ID. Releasing the energy bow generates different telegram data, so every PTM telegram contains the information that the bow was pressed or released. In addition, the radio telegram transmits the operating status of 4 contact nipples when activating the bow. This enables the identification of up to 2 appropriate switch rockers or up to 4 single pushbuttons.



„Long“ or „Short“ pushbutton operation (the time between pushing and releasing the push button) can be easily detected by the receiver. By doing that, applications such as dimming control or jalousie control including slat action are simple to implement.

### Features overview

<b>Power supply</b>	power generation by rocker operating Electro-dynamic Power Generator
<b>Antenna</b>	integrated PCB antenna
<b>Frequency</b>	868.3 MHz
<b>Data rate / Modulation</b>	125 kbps / FSK
<b>Channels</b>	2 with 4 action states each (upper/lower pushbutton is pressed/released)
<b>Transmission range</b>	300 m free field
<b>Energy bow travel/Operating force</b>	1.8 mm / typ. 8 N (at room temperature)
<b>Number of operations at 25°C</b>	typ. 100.000 actuations tested according to EN 60669 / VDE 0632
<b>Module dimensions (inclusive rotation axis and energy bow)</b>	40.0 x 40.0 x 11.2 mm
<b>Operating temperature</b>	- 25 up to + 65 °C

Radio signals are event controlled (pushbutton is pressed / is released) with button code and unique module identification (fixed 32 bit ID).